

VIVAX VOX

Ean code

Model : BS-810

3856005199372





Bluetooth Karaoke Speaker, USB player; MP3; PLL FM with FM station memory; 1x Wireless Microphones with batteries + 1x Remote control with batteries, RCA LINE in 3.5mm, USB+TF Card; 80W RMS Audio output (2x 8" Bass speaker + 1x 2" tweeter), 7Ah Rechargeable battery; Deep and powerful bass sound, Battery charging, Up to 7 hours of playback on battery power (medium volume); LED changeable light; 2x MIC input + Guitar input; TWS Function (Pairing two speakers); Karaoke function

| SPECIFICATIONS | |
|---------------------------|---|
| PLL FM Radio | Yes |
| AM Radio | - |
| Auto Radio search & Store | Yes |
| Programme memories | 30 |
| CD | No |
| Remote controler | Yes (with included 2x AAA Batteries) |
| LCD Display | Yes + button illumination |
| BBS (Bass boost sound) | Yes |
| Equalizer function | Yes, Preset sounds: Pop, Rock, Jazz, Classic, Flat, Manual adjust Bass/Treble |
| Clock | - |
| Auto ON/OFF | Yes |
| Amplifier | 80W RMS |
| Frequency range | 40Hz-18kHz +/- 3dB S/N:>75dB, Distortion: <0,1% 1kHz,1W |
| MULTIMEDIA | |
| MP3/WMA/FLAC/WAV/AAC | Yes / Yes / Yes / No / No |
| | |
| Other | TWS (True Wireless Stereo) - Pairing two speakers for louder and wider sound; 1x Wireless microphones, LIGHT MODE button for changing LED lighting; 2x microphone + 1x Guitar input, Mic priority function with Volume and Echo effect adjustments, Equalizer modes |

^{*} Due to different formats and codec format version, it is possible that all specified formats will not be supported. The manufacturer is not responsible for a such problems and it is not considered a malfunction of the device.



| TERMINALS | |
|--------------------------------------|--|
| AUX-IN / AUX Out | Yes, 3,5mm / No |
| STEREO HEADPHONE in | No |
| USB | Yes / MP3 Reproduction |
| FM Antenna | Yes, Audio kabel 3.5mm |
| SD/MMC | Yes, TF Card |
| Power On/Off switch | Yes |
| Wireless MIC / MIC1 / MIC2 / Guitar | Yes / Yes / Yes / Yes |
| POWER / DIMENSIONS | |
| Audio Power | 80W RMS |
| Speakers | 2x 8" 50W/4ohm Bass 1x 2" 15W/8ohm Tweeter |
| W x H x D unit dimension | 313 x 715 x 328 mm |
| W x H x D box dimension | 375 x 810 x 360 mm |
| Weight Gross/Not | 13.4 kg / 15,7 kg |
| Power | Lithium Battery 12V/7Ah / AC100-240V 5 |
| Charging | Yes, approx. 7h |
| ACCESSORIES | |
| Instruction manual | English, Croatian, Serbian, Macedonian, — Albanian. Slovenian + local market languages |
| Remote controller | Yes (Batteries 2x AAA included) |
| Wireless microphone / Wired micropho | on Yes 1x / No (Batteries 2xAA included) |

^{*} Product specifications are subject to change without notice.